

## GETTING STARTED WITH RUND00 · HARDWARE SET-UP

# Set Up Your Receipt Printer

Star Micronics TSP100IV, box to first receipt. The whole thing in three moves, plus the fastest fixes.

## THE WHOLE SETUP IN THREE MOVES

1

**Unbox & load paper**

Power it on, drop the roll in.  
Feeds off the bottom, out the front.

**Blank receipt = roll upside down**

2

**Get it on the network**

Wired is most reliable. No port nearby? Wi-Fi works the same.

**Ethernet or Wi-Fi**

3

**CloudPRNT & test**

Turn on CloudPRNT, send Rundoo the MAC, run a test sale.

**A receipt slides out**

**Print the self-test**

- 1 Flip the power switch **off**
- 2 Hold down the **Feed** button
- 3 Still holding, flip power back **on**
- 4 Let go. The sheet has the **IP** and **MAC**

**CloudPRNT: get these right**

**device.stario.online/cloudprnt/rndo**

Password **rundoo** (default is public) · Polling Time **1** sec · wireless printers send the **LAN** MAC, not the WLAN one.

**Lost connection to Stario?** Power the printer off for about 30 seconds, then hold the **Feed** button while powering it back on to run a self-print. That confirms it rejoined the network, and printing resumes on its own.

**Set up but not printing?** Nine times out of ten the printer and Rundoo are on different networks. Put them on the same one. Still stuck: re-check the Server URL, or see [Printer troubleshooting](#).